
ADAPTOR DATASHEET



2.4MM(MALE)-GPO(SMP)(FEMALE)

2.4/GPO-JK



*Dimensions are in mm

Configuration	
Connector 1 Type	2.4mm Male
Connector 1 Impedance	50 Ohms
Connector 1 Polarity	Standard
Connector 2 Type	GPO(SMP) Female
Connector 2 Impedance	50 Ohms
Connector 2 Polarity	Standard
Connector Mount Method	None
Adapter Body Style	Straight
-	DC to 40 GHz
Frequency Insertion Loss (dB) Return Loss	DC to 40 GHz ≤ 0.05 xSqt.(f_GHz)
Frequency	DC to 40 GHz ≤ 0.05 xSqt.(f_GHz) 1.25
Frequency Insertion Loss (dB) Return Loss	DC to 40 GHz ≤ 0.05 xSqt.(f_GHz) 1.25
Frequency Insertion Loss (dB) Return Loss Materials Information	DC to 40 GHz ≤ 0.05 xSqt.(f_GHz) 1.25
Frequency Insertion Loss (dB) Return Loss Materials Information Center Contact	DC to 40 GHz ≤ 0.05 xSqt.(f_GHz) 1.25 CuBe Gold Plated
Frequency Insertion Loss (dB) Return Loss Materials Information Center Contact Outer Contact	DC to 40 GHz ≤ 0.05 xSqt.(f_GHz) 1.25 CuBe Gold Plated Stainless Steel & CuBe Gold Plated
Frequency Insertion Loss (dB) Return Loss Materials Information Center Contact Outer Contact Body	DC to 40 GHz ≤ 0.05 xSqt.(f_GHz) 1.25 CuBe Gold Plated Stainless Steel & CuBe Gold Plated Stainless Steel
Frequency Insertion Loss (dB) Return Loss Materials Information Center Contact Outer Contact Body Dielectric	DC to 40 GHz ≤ 0.05 xSqt.(f_GHz) 1.25 CuBe Gold Plated Stainless Steel & CuBe Gold Plated Stainless Steel

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Gwave Technology Co.,Ltd.

No.33 Building,Hanjiachuan Yard,Haidian District,Beijing
China(100094) www.gwave-tech.com

Tel.: +86 10 62450051/52 Fax: +86 10 62450053 Email: gwave@gwave-tech.com

Page

1 / 1